

SR-32 Indoor Siren

Stay Alert to
Protect Your Premises



- Siren output level is 104dB at 1 meter
- Elegant, modern design
- Wireless, lightweight, easy to install

SR-32 is a battery-operated wireless indoor siren, generating a loud 104-decibel siren to alert users to possible intruders, emergencies, and safety incidents. The multi-functional indoor siren can work with the control panel to emit entry and exit delay beeps. The SR-32 generates unique alarm sounds for fire and burglary to audibly inform the user of the type of danger at hand.

Encased in an elegant, modish design, the SR-32 will effortlessly fit in your home décor. SR-32 is lightweight and easy to install, giving Users the flexibility to install it anywhere in the house. SR-32's tamper-deterrent feature also protects against unauthorized removal or sabotage.

Features

- Siren output level is 104dB at 1 meter
- Unique alarm sounds for fire and burglary
- Lightweight and flexible to install
- Programmable siren duration of 3/5/10 minutes
- Sound notifications of arming, disarming, and low battery status
- Smaller, visually pleasing design
- Cover tamper protection prevents unauthorized removal and sabotage
- Regular supervision signals to check system integrity
- Low battery detection
- Compatible with Vesta F1 Alarm Panels
- Compliant with CE requirement
- EN50131 Grade2, Class II certified

Specifications

SR-32-F1

Frequency	433 MHz / 868 MHz
Power Source	1.5V, D Alkaline battery x 2
Battery Life	3 years*
Siren Output	104 dB at 1 meter
Operating Temperature	-10°C to 45°C (14°F to 113°F)
Operating Humidity	Up to 85% non-condensing
Dimensions	212.5 mm x 179 mm x 53 mm